



Flush Mount for Gooseneck Microphone GEN-FMC/FMD

Features:

- Built-in microphone socket, suitable for GEN-MXXX series 6-pin gooseneck microphone
- Compact desktop microphone with a low-profile design for neat and unobtrusive installation.
- Optional capacitive touch button for microphone mute/unmute operation.
- Integrated touch button supports remote control through external equipment.
- LED status indicator on the touch button with White (Active) and Red (Mute) indication.
- Operates on 24–48 V DC Phantom Power.
- Audio output available through 3-pin XLR or 3-pin Phoenix (Euroblock) connector.
- Secure locking mechanism prevents accidental removal of the microphone after installation.
The microphone can only be removed after unlocking.
- Built-in RF (Radio Frequency) filter to minimize interference from wireless devices.
- Integrated rubber vibration isolators reduce noise caused by vibrations on the mounting surface.



Pluggable gooseneck Microphone GEN-MXXX

Item	GEN-M600	GEN-M485	GEN-M410	GEN-M330	GEN-M220
Directivity	Cardioid	Cardioid	Cardioid	Cardioid	Cardioid
Microphone Type	Condenser	Condenser	Condenser	Condenser	Condenser
Sensitivity	-46 dBV / Pa	-46 dBV / Pa	-46 dBV / Pa	-46 dBV / Pa	-46 dBV / Pa
Frequency Response	30 Hz ~ 20 kHz	30 Hz ~ 20 kHz	30 Hz ~ 20 kHz	30 Hz ~ 20 kHz	30 Hz ~ 20 kHz
Equivalent Noise	20 dBA (SPL)	20 dBA (SPL)	20 dBA (SPL)	20 dBA (SPL)	20 dBA (SPL)
Signal-to-Noise Ratio (Ref.)	≥ 96 dB	≥ 96 dB	≥ 96 dB	≥ 96 dB	≥ 96 dB
Maximum SPL	125 dB (1 kHz, THD < 3%, 1 kΩ load)	125 dB	125 dB	125 dB	125 dB
Conference Unit Connection	Mini 6-pin	Mini 6-pin	Mini 6-pin	Mini 6-pin	Mini 6-pin
Input Impedance	2 kΩ	2 kΩ	2 kΩ	2 kΩ	2 kΩ